

PIR Camera w/ Built-in DVR

All-in-one Camera & DVR

in focus...

- ▶ CMOS, 200 Mega Pixel; 420 TV Line
- ▶ Built-In Motion Detection DVR
- ▶ 2.8mm Board Lens 120° FOV
- ▶ 13 IR LEDS @ 850nm 25' Range
- ▶ Comes with Mini Alarm Siren
- ▶ Internal Li-ion Rechargeable Battery
- ▶ 8GB SD Card Included



[PIR1003DVR]

specifications | PIR1003DVR

Model	LSMDS06
Items	Data
Power supply	DC 5V
Pixels	500mA-800mA
AV Out volt	1Vp-p
AV out impedance	75Ω =
TV Mode	PAL / NTSC
Internal camera	CMOS , 200 Mega Pixel
Lens	2.8mm Board Lens
Trigger for record	Motion detection
Trigger for alarm	Motion detection + PIR detection (optional)
PIR detection distance	≤8M
View angle	≤120 degree
Record Frame	PAL:10 f/s NTSC:10f/s
AVI Resolution	320 X 240
JPEG resolution	640 X 480
Horizontal resolution	420 TV Line
Memory	Flash memory and SD Card
SD card capacity	≤8G byte
OSD	English
Alarm chip	Fixed code :PT2262 / Study code: SC1527
Surge resistance	4. 7MΩ(optional)
Data code	D1 low ,D2 high,D3 empty,D4 empty
Wireless frequency	315MHZ/433MHZ (optional)
Li-battery capacity	1800MAH
Battery recharge	>6 hours
Battery discharge	>3 hours
AC adapter	AC/110 – 240V ,50-60HZ,DC5V ,1.5A
RC distance	≤8M
IR distance	5M-8M
IR wavelength	850NM
8G SD card using time	Common conditions: AVI video recording for 3-5days, snapshot for 15days

WWW.SCDLINK.COM

1 SECURITY CAMERAS DIRECT WAY
LULING, TX 78648
PHONE: 800.316.6027
830.401.7000
FAX: 830.875.9010

SECURITY CAMERAS
DIRECT